PM862

Fuente de alimentación, 24 VCC, 1,5 A

This efficiency cost effective power supply is ideal for use in Fire, Access control and general security applications.

Featuring a regulated 27.6 Vdc output supplying continuous full rated current to load plus additional current for charging two x 12V standby batteries.

The highly efficient switch mode design ensures low operating costs, generates less heat and with a small physical size increases the room available for additional PCBs or cables. The modular construction simplifies maintenance.



Detalles

- Indicadores de fallo y presencia de red eléctrica
- Desconexión de la batería para evitar una descarga profunda
- Tamperswitch
- Salidas de fallo
- Fusible de red y CC
- Carcasa de acero con recubrimiento en polvo

PM862

Fuente de alimentación, 24 VCC, 1,5 A

Especificaciones técnicas

General

Fuse(s)	Entrada de 230 VCA, 2 A; salida de 12/24 V, 2 A

Electrical

Mains input	230 VAC
Operating voltage	50/60 Hz ±10%

Output

Power output voltage	27.6 VDC
Power output current mains	2 A

Battery

Max. Battery capacity	7.2 Ah (x2)
Battery charge current	0.5 A
Battery recharge time	20 hours
Battery disconnect voltage	19.6 ±0.2 VDC

Physical

Physical dimensions	330 x 275 x 80 mm (W x H x D)
Colour	White
Form factor	Steel cabinet

Environmental

Operating temperature	-10 to +40°C
Relative humidity	95%

Regulatory

Compliancy	CE, REACH, RoHS 2, WEEE

Salida de carga

	1.5 A

Salida de colector abierto

	Circuito abierto ON
	fallo o fallo de la red eléctrica
	- 0 V - 100 mA

Carcasa (acero) con recubrimiento en polvo

	1.2 mm

Como empresa innovadora, Kidde Global Solutions se reserva el derecho de modificar las especificaciones de los productos sin previo aviso. Para conocer las últimas especificaciones de los productos, visite la Web de es.firesecurityproducts.com o póngase en contacto con su comercial.

Last updated on 12 November 2026 - 18:57